

Manual Changeover Switch

Introduction

A range of manual changeover switches, mounted in enclosures.

These are normally used to switch between mains and generator supply in conjunction with a manually operated (key or hand start) generator. However, they can be used to switch between any two supplies or to switch any single supply between two outputs.

All current ratings quoted are AC23 ratings @ 415v (40 degrees C).



Standard features (100A and above)

- Rotary switch
- Sheet Steel Inclosure enclosure
- IP65 (IP54 with cable glands fitted)

Standard features (125A and above)

- “Load break style” switch
- Door interlock with 3 position padlockable

Handle

- Load links or bridging bars fitted to switch
- Proprietary manufactured IP55 sheet steel enclosure with hinged, lockable front access door finished in grey RAL7032.
- Gland plates fitted top and bottom

Dimensions

	Hight	Width	Depth
0 - 45 Amp	300	200	150
63 - 125 Amp	400	300	200
160 - 200 Amp	600	400	300
250 - 315 Amp	700	500	300
400 - 550 Amp	800	600	300
630 - 800 Amp	1200	800	400
1000 - 1600 Amp	1200	800	400
2500 - 3150 Amp	1800	800	600

Optional Extras

- Auxilary Contacts
- Aluminium Gland Plates
- LED Indication Lights

Blades Power Generation

Tel: +44 (0)1453 821322 e-mail sales@bladespowergeneration.com

<http://www.bladespowergeneration.co.uk>

67 Devereaux Crescent, Ebley, Stroud, Gloucestershire, GL5 4PX

We reserve the right to amend specifications without prior notice.